

HME PRO850 Band 2 / A Preprogrammed Frequencies

Base TX Frequency Groups

Band 2, P-Group

Group/Channel	Freq. (MHz)
P1	508.250
P2	509.750
P3	515.250
P4	520.500

Band 2, S-Group

Group/Channel	Freq. (MHz)
S1	508.500
S2	514.250
S3	515.750
S4	521.250

Band 2, T-Group

Group/Channel	Freq. (MHz)
T1	509.250
T2	514.500
T3	520.250
T4	521.750

User frequencies are designated U1 – U16 and are initially set to 506.000 MHz

Within groups, all frequencies are compatible with each other.

Base TX and Beltpac TX groups are independent of each other. Thus all Base TX frequencies are compatible with all Beltpac TX frequencies.

Beltpac TX Frequency Groups

Band A, P-Group

Group/Channel	Freq. (MHz)
P1	651.375
P2	652.000
P3	653.125
P4	655.000
P5	655.375
P6	656.375
P7	659.125
P8	661.125
P9	663.750
P10	664.250
P11	665.000
P12	666.625

Band A, S-Group

Group/Channel	Freq. (MHz)
S1	651.250
S2	651.875
S3	653.000
S4	654.875
S5	655.250
S6	656.250
S7	659.000
S8	661.000
S9	663.625
S10	664.125
S11	664.875
S12	666.500

Band A, T-Group

Group/Channel	Freq. (MHz)
T1	651.500
T2	652.125
T3	653.250
T4	655.125
T5	655.500
T6	656.500
T7	659.250
T8	661.250
T9	663.875
T10	664.375
T11	665.125
T12	666.750

User frequencies are designated U1 – U16 and are initially set to 650.000 MHz



HM ELECTRONICS, INC.
14110 Stowe Drive, Poway, CA 92064 USA